

# MA7200 integrated amplifier

- Offering 200 Watts per channel and 14 total inputs, the space-saving MA7200 Integrated Amplifier can easily become the core of your 2-channel home audio system.
- Comes with our advanced DA2 Digital Audio Module that supports high resolution digital music playback of up to DSD512 and 24-bit/192kHz. An HDMI (ARC) input will extract the best sound possible from your compatible TV.
- Features our new McIntosh Monogrammed Heatsinks™ that are so efficient at dissipating heat that they warrant bearing the McIntosh “Mc” logo.
- Utilizes new, more powerful control microprocessors and some of the latest audio-grade circuit components.
- Full of numerous McIntosh technologies including Autoformers, Power Guard®, Sentry Monitor™, Home Theater PassThru, High Drive headphone amplifier with Headphone Crossfeed Director (HXD®) and Power Control.



Not available in the US and Canada. (Please see the MAC7200 Receiver.)



Core of a 2-Channel Home Audio System

McIntosh®

# MA7200 integrated amplifier

## Power Output:

200 Watts per channel. McIntosh Autoformers ensure all speakers receive the full 200 Watts regardless if they are 2, 4 or 8 Ohm impedance.

## Total Harmonic Distortion:

0.005% maximum from 20Hz to 20kHz

## Tone Controls:

Bass and Treble

## Headphone Amplifier:

1/4" High Drive with Headphone Crossfeed Director (HXD®). Powers all headphones from 20 to 600 Ohms.

## Analog Inputs:

5 Unbalanced  
1 Balanced  
1 Moving Coil  
1 Moving Magnet

## Digital Inputs:

2 Coax  
2 Optical  
1 USB  
  
1 MCT (used with McIntosh MCT series SACD/CD Transports)  
1 HDMI (ARC)

## Home Theater PassThru:

Allows for seamless interfacing with a Home Theater system.

## Overall Dimensions (W x H x D):

17-1/2" (44.5cm) x 7-5/8" (19.37cm) x 22" (55.88cm) including knobs, connectors and cables

## Weight:

75 lbs (34.1kg) net,  
93 lbs (42.3kg) in shipping carton

## For the Consumer's Protection:

In order to ensure the highest level of customer satisfaction, new McIntosh products may only be purchased from an Authorized McIntosh Dealer; and, with certain limited exceptions may only be purchased over-the-counter or delivered and installed by the Authorized McIntosh Dealer. McIntosh does not warrant, in any way, products that are purchased from anyone who is not an Authorized McIntosh Dealer, or that have had their serial numbers altered or defaced.



## Companion Products

The DS200 Streaming DAC, MCT500 SACD/CD Transport, MT5 Precision Turntable, and XR50 Bookshelf Loudspeakers are logical companions for the MA7200 Integrated Amplifier. Your Authorized Dealer can provide additional information on other McIntosh product combinations.

To learn more, please call us at 1.800.538.6576.

# McIntosh®